

DIGITAL COUNTER (Totaliser)



- 1) MODEL : COUNTER - 0249. Size : (48 x 96 x 75) mm, Refer Size (4) table.
- 2) MODEL : COUNTER - 0277. Size : (72 x 72 x 74) mm, Refer Size (2) table.
 - LED display height 0.5” in Counter - 0249 & 0.39” in Counter - 0277.
 - Range : 6 Digit, 999999 Counts. ● Count retention in memory at power failure.
 - Input Frequency : 30 Hz / 4 KHz – Selectable.
 - Input Sensor : PNP / NPN Proximity / Photo sensor, encoders, solid state devices, potential free contact - Selectable. ● Accuracy : 0.05 %
 - Reset : Front panel reset key (enable / disable facility) & rear terminal for remote reset.
 - Supply : 90 to 250 VAC/DC @ 50/60 Hz. (24 VAC/DC provided on request)

DIGITAL COUNTER (Totaliser with Scale Factor)



- 1) MODEL : COUNTER - 0349 SC. Size : (48 x 96 x 75) mm, Refer Size (4) table.
- 2) MODEL : COUNTER - 0377 SC. Size : (72 x 72 x 74) mm, Refer Size (2) table.
 - RANGE : 6 Digit , 99999.9 Counts. ● Scale Factor : 6 digit : 0.00001 to 999.999
 - LED display height 0.5” in Counter-0349 SC, and 0.39” in Counter-0377 SC height.
 - Input Frequency : 30 Hz / 4 KHz – Selectable. ● Count retention in memory at power failure.
 - Input Sensor : PNP / NPN Proximity / Photo sensor, encoders, solid state devices, potential free contact - Selectable. ● Accuracy : 0.05 %
 - Reset : Front panel reset key (enable / disable facility) & rear terminal for remote reset.
 - Supply : 90 to 250 VAC/DC @ 50/60 Hz. (24 VAC/DC provided on request)

OVER ALL MOUNTING DIMENSIONS (in mm)

		Panel Cut out			
A	B	C	D	E	F
SIZE - (4)	48	96	75	10	46

		Panel Cut out			
		DIM			
SIZE	A	B	C	D	F
SIZE - (1)	96	96	74	10	92
SIZE - (2)	72	72	74	10	69
SIZE - (3)	48	48	92	4	46